Solid core rectangle zero sequence leakage current transformerr


Model: ZCT14032BT

Used for residual current detection, with good linearity and high sensitivity. Widely used in dangerous goods places, high-rise buildings, public places and residential buildings and the unit power supply system of the building, there are lead wire or the compression terminal two output modes optional

Technical indexes:


Fair resistance: UL94-V0

Work temperature: -25 \sim +70 $^{\circ}$ C Storage temperature: -35 \sim +85 $^{\circ}$ C Delectric strength: 3.5 KV 50Hz 1min




Primary rated test current	1000	m A
Secondary rated output current	0.5	mA
Turns ratio	1: 2000	
Rated continuous thermal current	2000	mA
Accuracy	1	%
Sampling resistance	< 1 K	Ω
Weight	1000	g


Wiring schematic diagram:




Outline size: (in:mm):




Front view





Put the lead wire (three-phase example)



Bottom view